

BRANCH PANEL: LP-1A1									
Location: TOWER A LEVEL 1 ELEC A125				Fed From: LRP2A1		Wires: 4W + G			
Main Bus: 225 A				Enclosure: NEMA 1		Ground Bus: YES			
MCB: 200 A				Bus Type: COPPER		Isolated Ground Bus: NO			
Voltage: 120/208 Wye				Mounting: WALL MOUNTED		200% Neutral: NO			
AIC Rating: 10 kA				Feed Through Lugs: NO					

CKT	Circuit Description	Load Classification	Trip	Poles	A	B	C	Poles	Trip	Load Classification	Circuit Description	CKT		
1	POWER TREATMENT SINGLE	RCPTS	20 A	1	540 VA 360 VA				20 A	RCPTS	SPA LOUNGE A113 MISC	2		
3	POWER FIRE FLUE FAN AND	Power	20 A	1		150 VA 360 VA			20 A	RCPTS	SPA LOUNGE A113 MISC	4		
5	POWER FIRE PIT	HEAT	20 A	1			200 VA 540 VA		20 A	RCPTS	SPA LOUNGE A113	6		
7	SPARE		20 A	1	0 VA 180 VA				20 A	RCPTS	TOWER A L1 MISC RCPTS	8		
9	LOCKER ROOM RCPTS	RCPTS	20 A	1		720 VA 540 VA			20 A	RCPTS	SPA TREATMENT DOUBLE...	10		
11	LOCKER ROOM RCPTS	RCPTS	20 A	1			1080... 540 VA		20 A	RCPTS	SPA TOILET A108	12		
13	LOCKER ROOM RCPTS	RCPTS	20 A	1	540 VA 360 VA	0 VA 0 VA			20 A	RCPTS	SPA TREATMENT DOUBLE...	14		
15	SPARE	--	20 A	1					20 A	--	SPARE	16		
17	SPARE	--	20 A	1		0 VA 0 VA	0 VA 0 VA		20 A	--	SPARE	18		
19	FITNESS A121 RCPTS	RCPTS	20 A	1	900 VA 0 VA				20 A	--	SPARE	20		
21	FITNESS A121 TREADMILL	RCPTS	20 A	1		1000... 0 VA			20 A	--	SPARE	22		
23	FITNESS A121 TREADMILL	RCPTS	20 A	1		1000... 360 VA	1	20 A	RCPTS	TOWER A L3 CORR RCPTS	24			
25	FITNESS A121 CYCLE RCPT	RCPTS	20 A	1	1500... 360 VA				20 A	RCPTS	TOWER A L3 CORR RCPTS	26		
27	FITNESS A121 BKE	RCPTS	20 A	1		1000... 360 VA			20 A	RCPTS	TOWER A L2 CORR RCPTS	28		
29	FITNESS A121 ROWING	RCPTS	20 A	1		1000... 360 VA			20 A	RCPTS	TOWER A L2 CORR RCPTS	30		
31	FITNESS A121 MIRROR RCPT	RCPTS	20 A	1	500 VA 0 VA				20 A	RCPTS	TOWER A L2 CORR RCPTS	32		
33	YOGA A119 RCPTS	RCPTS	20 A	1		360 VA 0 VA			20 A	--	SPARE	34		
35	STAR 028 A143A205A305	RCPTS	20 A	1			540 VA 0 VA	1	20 A	RCPTS	STAR 018 A02/A302	36		
37	STAR 02A RCPTS	RCPTS	20 A	1	540 VA 0 VA				20 A	RCPTS	STAR 01B A02/A302	38		
39	TOWER A L1 MISC RCPTS	RCPTS	20 A	1		600 VA 540 VA			20 A	RCPTS	STAR 01A /	40		
41	TOWER A L1 MISC RCPTS	RCPTS	20 A	1			720 VA 540 VA	1	20 A	RCPTS	STAR 01A /	42		
43	SPARE		20 A	1	0 VA 0 VA				20 A			44		
45	SPARE		20 A	1		0 VA 0 VA			20 A			46		
47	SPARE		20 A	1		0 VA 0 VA			20 A			48		
49	SPARE		20 A	1	0 VA 0 VA				20 A			50		
51	SPARE		20 A	1	0 VA 0 VA				20 A			52		
53	SPARE		20 A	1	0 VA 0 VA				20 A			54		
55	SPARE		20 A	1	0 VA 266 VA			0 VA 432 VA	2	20 A	HEAT	UHKA	56	
57	TOWER A L1 ENTRY LOBBY	RCPTS	20 A	1		1080... 266 VA			20 A	MTRS	FCU-A-1,2	58		
59	TOWER A L1 ENTRY	RCPTS	20 A	1			800 VA 1000...	1	20 A	MTRS	SLIDING DOORS	60		
Total Load:					6646 VA					7708 VA				
Total Amps:					50 A					66 A				
										79 A				

LP-1A1 LOAD SUMMARY									
Load Classification	Connected Load	*Demand Factor	Estimated Demand	Panel Totals					
RCPTS	20220 VA		15110 VA						
MTRS	1532 VA		1532 VA	Total Conn. Load: 22966 VA					
HEAT	1164 VA		1164 VA	Total Est. Demand: 17856 VA					
Power	50 VA		50 VA	Total Conn.: 16 A					
				Total Est. Demand: 50 A					

Notes:
*See Demand Factor Table

BRANCH PANEL: MPH-1A1									
Location: TOWER A LEVEL 1 ELEC A110				Fed From: MPH-P2A1		Wires: 4W + G			
Main Bus: 400 A				Enclosure: NEMA 1		Ground Bus: YES			
MCB: 400A				Bus Type: COPPER		Isolated Ground Bus: NO			
Voltage: 480/277 Wye				Mounting: WALL MOUNTED		200% Neutral: NO			
AIC Rating: 25 kA				Feed Through Lugs: NO					

CKT	Circuit Description	Load Classification	Trip	Poles	A	B	C	Poles	Trip	Load Classification	Circuit Description	CKT	
1	FPT A-1-3	MTRS	20 A	1	610 VA 1600...			3	20 A	MTRS	AHU- L1-1	2	
3	FPT A-1-2 & FPT A-1-3	MTRS	20 A	1		1330... 1600...						4	
5	FPT A-1-2	MTRS	20 A	1			610 VA 1600...					6	
7	FPT A-1-3	MTRS	20 A	1	1220... 0 VA			1	20 A		SPARE	8	
9	FPT A-1-6	MTRS	20 A	1		1470... 0 VA					SPARE	10	
11	FPT A-1-7	MTRS	20 A	1			610 VA 0 VA	1	20 A		SPARE	12	
13	FPT A-1-10	MTRS	20 A	1		1830... 0 VA					SPARE	14	
15	FPT A-1-5	MTRS	20 A	1		1220... 0 VA					SPARE	16	
17	EF-A-1,1	MTRS	20 A	1			803 VA 0 VA	1	20 A		SPARE	18	
19	SPARE		20 A	1	0 VA 0 VA				20 A		SPARE	20	
21	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	22	
23	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	24	
25	SPARE		20 A	1	0 VA 0 VA				20 A		SPARE	26	
27	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	28	
29	SPARE		20 A	1	0 VA 0 VA		0 VA 0 VA	1	20 A		SPARE	30	
31	SPARE		20 A	1	0 VA 0 VA				20 A		SPARE	32	
33	SPARE		20 A	1	0 VA 0 VA		0 VA 0 VA	1	20 A		SPARE	34	
35	SPARE		20 A	1			0 VA 0 VA		20 A		SPARE	36	
37	PANEL MPH-6A1	Spare...	400 A	3	6806... 0 VA			1	20 A		SPARE	38	
39						6806... 0 VA			20 A		SPARE	40	
41							6806... 0 VA	1	20 A		SPARE	42	
43	SPARE		20 A	1	0 VA 0 VA				20 A		SPARE	44	
45	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	46	
47	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A		SPARE	48	
49	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	50	
51	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	52	
53	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A		SPARE	54	
55	SPARE		20 A	1	0 VA 0 VA				20 A		SPARE	56	
57	SPARE		20 A	1		0 VA 0 VA			20 A		SPARE	58	
59	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A		SPARE	60	
Total Load:					73349 VA					73709 VA			
Total Amps:					266 A					267 A			

MPH-1A1 LOAD SUMMARY									
Load Classification	Connected Load	*Demand Factor	Estimated Demand	Panel Totals					
MTRS	218770 VA		218770 VA	Total Conn. Load: 218770 VA					
				Total Est. Demand: 218770 VA					
				Total Conn.: 263 A					
				Total Est. Demand: 263 A					

Notes:
*See Demand Factor Table

BRANCH PANEL: LP-1A2									
Location: TOWER A LEVEL 1 KITCHEN				Fed From: T-P2A2-L		Wires: 4W + G			
Main Bus: 400 A				Enclosure: NEMA 1		Ground Bus: YES			
MCB: 400A				Bus Type: COPPER		Isolated Ground Bus: NO			
Voltage: 120/208 Wye				Mounting: WALL MOUNTED		200% Neutral: NO			
AIC Rating: 10 kA				Feed Through Lugs: NO					

CKT	Circuit Description	Load Classification	Trip	Poles	A	B	C	Poles	Trip	Load Classification	Circuit Description	CKT	
1	POWER TOILET A108 RCPTS	RCPTS	20 A	1	720 VA 0 VA				1	20 A	--	SPARE	2
3	RCPTS CORRIDOR TO	RCPTS	20 A	1		540 VA 0 VA			1	20 A	--	SPARE	4
5	RCPTS PRIVATE DINNING	RCPTS	20 A	1			360 VA 0 VA	1	20 A	--	SPARE	6	
7	RCPTS PRIVATE DINNING	RCPTS	20 A	1		360 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	8	
9	SPARE		20 A	1					1	20 A	--	SPARE	10
11	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	12	
13	SPARE		20 A	1	0 VA 0 VA				1	20 A	--	SPARE	14
15	SPARE		20 A	1		0 VA 0 VA			1	20 A	--	SPARE	16
17	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	18	
19	SPARE		20 A	1	0 VA 0 VA	0 VA 0 VA			1	20 A	--	SPARE	20
21	SPARE		20 A	1				0 VA 0 VA	1	20 A	--	SPARE	22
23	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	24	
25	SPARE		20 A	1	0 VA 0 VA				1	20 A	--	SPARE	26
27	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	28	
29	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	30	
31	SPARE		20 A	1	0 VA 0 VA				1	20 A	--	SPARE	32
33	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	34	
35	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	36	
37	SPARE		20 A	1	0 VA 0 VA	0 VA 0 VA			1	20 A	--	SPARE	38
39	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	40	
41	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	42	
43	SPARE		20 A	1				0 VA 0 VA	1	20 A	--	SPARE	44
45	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	46	
47	SPARE		20 A	1				0 VA 0 VA	1	20 A	--	SPARE	48
49	SPARE		20 A	1	0 VA 0 VA				1	20 A	--	SPARE	50
51	SPARE		20 A	1		0 VA 0 VA	0 VA 0 VA	1	20 A	--	SPARE	52	
53	SPARE		20 A	1				0 VA 0 VA	1	20 A	--	SPARE	54
55	SPARE		20 A	1	0 VA 0 VA	0 VA 0 VA			1	20 A	--	SPARE	56
57	SPARE		20 A	1			0 VA 0 VA	1	20 A	--	SPARE	58	
59	SPARE		20 A	1				0 VA 0 VA	1	20 A	--	SPARE	60
Total Load:					1080 VA	540 VA	3 A						
Total Amps:					9 A	5 A	3 A						